

## A NOTE ON COMMUTATIVITY OF AUTOMORPHISMS

M.S. SAMMAN  
M. ANWAR CHAUDHRY  
A.B. THAHEEM

Department of Mathematical Science  
King Fahd University of Petroleum and Minerals  
Dhahran 31261, SAUDI ARABIA

(Received March 26, 1996)

**ABSTRACT.** Let  $\alpha$  and  $\beta$  be automorphisms of a ring satisfying the equation  $\alpha + \alpha^{-1} = \beta + \beta^{-1}$ . In this paper we prove some results where this equation itself implies the commutativity of  $\alpha$  and  $\beta$ .

**KEY WORDS AND PHRASES:** Unital ring, nilpotent element, automorphism

**1991 AMS SUBJECT CLASSIFICATION CODES:** Primary 16W20; Secondary 46L40

### 1. INTRODUCTION

The equation

$$\alpha + \alpha^{-1} = \beta + \beta^{-1}, \quad (*)$$

where  $\alpha$  and  $\beta$  are automorphisms of a ring  $R$ , has been of considerable interest during recent years (see e.g [1,2]). The study of this equation becomes simpler when an additional assumption of commutativity of  $\alpha$  and  $\beta$  is made. However, some situations have been identified where equation (\*) itself implies the commutativity of  $\alpha$  and  $\beta$ . For instance, it has been shown in [1, Corollary 3] that if  $R$  is a semiprime unital ring containing the element  $1/2$  and  $\alpha, \beta$  are inner automorphisms of  $R$  satisfying the equation (\*), then  $\alpha$  and  $\beta$  commute.

The purpose of this note is precisely to address the commutativity problem and prove certain results in this context. The main result (Theorem 2.1) is, in fact, a generalization of a result of Cater and Thaheem [3] proved for complex algebras, where the equation (\*) appears in a more general form:  $\alpha + m\alpha^{-1} = \beta + m\beta^{-1}$  for an appropriate integer  $m$ . The mappings of the type  $\alpha + m\alpha^{-1}$  occur in the studies of automorphisms of certain  $C^*$ -algebras (see for instance [3]). We show here (Theorem 2.1) that if  $R$  is a unital ring and  $\alpha$  and  $\beta$  are inner automorphisms of  $R$  induced by  $u$  and  $v$ , respectively, such that (i)  $\alpha(x) + m\alpha^{-1}(x) = \beta(x) + m\beta^{-1}(x)$ , for  $x = u, v$ , and (ii)  $\alpha\beta(x) = \beta\alpha(x)$ , for  $x = u, v$ , where  $R$  is  $(m^2 - 1)$ -torsion free, then  $\alpha$  and  $\beta$  commute. As a corollary (Corollary 2.2) we provide an alternate proof of a special case of Brešar's result [1, Corollary 3] when  $R$  has no nontrivial nilpotent elements. However as in Theorem 2.1, the equation (\*) here need not hold for all the elements of the ring.

We remark that the equation (\*) has been extensively studied for von Neumann algebras and  $C^*$ -algebras and for more information in this context we may refer to [4,5], which contain further references.

## 2. COMMUTATIVITY RESULTS

We begin with the following theorem which generalizes a result of Cater and Thaheem [3] proved for complex algebras. Our approach here is almost analogous to that of [3].

**THEOREM 2.1.** Let  $R$  be a unital ring and  $\alpha, \beta$  be inner automorphisms of  $R$  induced by  $u$  and  $v$ , respectively, such that

$$\alpha(x) + m\alpha^{-1}(x) = \beta(x) + m\beta^{-1}(x), \quad \text{for } x = u, v, \quad (i)$$

and

$$\alpha\beta(x) = \beta\alpha(x), \quad \text{for } x = u, v. \quad (ii)$$

If  $R$  is  $(m^2 - 1)$ -torsion free, then  $\alpha$  and  $\beta$  commute.

**PROOF.** Put  $k = u^{-1}vu v^{-1}$ . We first show that  $k$  commutes with  $u$  and  $v$ . Substituting  $x = v$  in (ii), we get  $uvu^{-1} = vuv^{-1}v^{-1}$ . We may rewrite this equation as

$$vu = uvk \quad (1)$$

or

$$vk = u^{-1}vu. \quad (2)$$

Also,

$$kv = u^{-1}vu v^{-1}v = u^{-1}vu. \quad (3)$$

It follows from (2) and (3) that  $kv = vk$ . Thus  $k$  and  $v$  commute. By symmetry,  $k$  and  $u$  also commute. Thus we can write (1) as

$$kuv = vu. \quad (4)$$

Substituting  $x = v$  in (i), we get

$$uvu^{-1} + mu^{-1}vu = (1 + m)v. \quad (5)$$

Multiplying (5) on the right by  $u$ , we get

$$uv + mu^{-1}vu u = (1 + m)vu. \quad (6)$$

It follows from (4) and (6) that

$$uv + mkvu = (1 + m)vu. \quad (7)$$

It follows from (4) and (7) that

$$uv + mk^2uv = (1 + m)kuv, \quad (8)$$

or what is the same

$$(mk - 1)(k - 1)uv = (mk^2 - mk - k + 1)uv = 0. \quad (9)$$

Since  $uv$  is invertible, we get from (9) that

$$mk^2 - mk - k + 1 = 0. \quad (10)$$

We observe from (4) that  $k^{-1}vu = uv$ . Repeating the above procedure with  $v$  in place of  $u$ ,  $u$  in place of  $v$  and  $k^{-1}$  in place of  $k$ , we get

$$(mk^{-1} - 1)(k^{-1} - 1) = 0. \quad (11)$$

Multiplying (11) on the left by  $mk$  and on the right by  $k$ , we obtain

$$(m^2 - mk)(1 - k) = m^2 - m^2k - mk + mk^2 = 0, \quad (12)$$

or what is the same

$$-mk^2 + mk + m^2k - m^2 = 0. \quad (13)$$

Adding (10) and (13), we get

$$(m^2 - 1)(k - 1) = 0. \quad (14)$$

Since  $R$  is  $(m^2 - 1)$ -torsion free, we get from (14) that  $k - 1 = 0$  or  $k = 1$ . This implies  $uv = vu$  and hence  $\alpha$  and  $\beta$  commute.

The following corollary gives an alternate proof of Brešar's result [1, Corollary 3] in the special case when  $R$  has no nontrivial nilpotent elements with an additional assumption that  $(\alpha\beta)(u) = (\beta\alpha)(u)$  and  $(\alpha\beta)(v) = (\beta\alpha)(v)$ . However, in our setting it is sufficient for equation (\*) to hold for some specific elements rather than all the elements of the ring to ensure the commutativity of  $\alpha$  and  $\beta$ .

**COROLLARY 2.2.** Let  $R$  be a unital ring with no nonzero nilpotent elements and  $\alpha, \beta$  be inner automorphisms of  $R$  induced by  $u$  and  $v$  respectively such that

$$\alpha(v) + \alpha^{-1}(v) = \beta(v) + \beta^{-1}(v) \quad (iii)$$

and

$$\alpha\beta(x) = \beta\alpha(x), \quad \text{for } x = u, v. \quad (iv)$$

Then  $\alpha$  and  $\beta$  commute.

**PROOF.** As in the proof of Theorem 2.1, put  $k = u^{-1}vuv^{-1}$ . Then  $k$  commutes with  $u$  and  $v$  follows from (iv) and consequently equation (4) holds. Then using (iii) and following a procedure similar to Theorem 2.1, we obtain that  $(k - 1)^2 = 0$ . Since  $R$  has no nonzero nilpotent elements, we get  $k - 1 = 0$  or  $k = 1$ . This proves that  $uv = vu$  and hence  $\alpha$  and  $\beta$  commute.

**REMARK 2.3.** (a) We observe that the main argument in proving the commutativity of  $\alpha$  and  $\beta$  has been to show that  $k = 1$ . In fact, somewhat weaker condition, namely that  $k$  belongs to the center of  $R$  would also ensure the commutativity of  $\alpha$  and  $\beta$ . Therefore, it would also be interesting to prove that  $k$  is in the center of  $R$ .

(b) It would be interesting to prove or disprove Theorem 2.1 for the case  $m = -1$ .

**ACKNOWLEDGMENT.** The authors gratefully acknowledge the support provided by King Fahd University of Petroleum and Minerals during this research.

#### REFERENCES

- [1] BREŠAR, M., On certain pairs of automorphisms of rings, *J. Austral. Math. Soc. (Series A)*, **54** (1993), 29-38.
- [2] BREŠAR, M., On the composition of  $(\alpha, \beta)$ -derivations of rings and applications to von Neumann algebras, *Acta Sci. Math.*, **56** (1992), 369-375.
- [3] CATER, F.S. and THAHEEM, A.B., On a pair of automorphisms of  $C^*$ -algebras, To appear in *Ren. Sem. Mat. Univ. Padova*.
- [4] THAHEEM, A.B., On certain decompositional properties of von Neumann algebras, *Glasgow Math. J.*, **29** (1987), 177-179.
- [5] THAHEEM, A.B., On a functional equation on  $C^*$ -algebras, *Funkcial. Ekvac.*, **31** (1988), 411-413.

## Special Issue on Modeling Experimental Nonlinear Dynamics and Chaotic Scenarios

### Call for Papers

Thinking about nonlinearity in engineering areas, up to the 70s, was focused on intentionally built nonlinear parts in order to improve the operational characteristics of a device or system. Keying, saturation, hysteretic phenomena, and dead zones were added to existing devices increasing their behavior diversity and precision. In this context, an intrinsic nonlinearity was treated just as a linear approximation, around equilibrium points.

Inspired on the rediscovering of the richness of nonlinear and chaotic phenomena, engineers started using analytical tools from "Qualitative Theory of Differential Equations," allowing more precise analysis and synthesis, in order to produce new vital products and services. Bifurcation theory, dynamical systems and chaos started to be part of the mandatory set of tools for design engineers.

This proposed special edition of the *Mathematical Problems in Engineering* aims to provide a picture of the importance of the bifurcation theory, relating it with nonlinear and chaotic dynamics for natural and engineered systems. Ideas of how this dynamics can be captured through precisely tailored real and numerical experiments and understanding by the combination of specific tools that associate dynamical system theory and geometric tools in a very clever, sophisticated, and at the same time simple and unique analytical environment are the subject of this issue, allowing new methods to design high-precision devices and equipment.

Authors should follow the Mathematical Problems in Engineering manuscript format described at <http://www.hindawi.com/journals/mpe/>. Prospective authors should submit an electronic copy of their complete manuscript through the journal Manuscript Tracking System at <http://mts.hindawi.com/> according to the following timetable:

Manuscript Due	February 1, 2009
First Round of Reviews	May 1, 2009
Publication Date	August 1, 2009

### Guest Editors

**José Roberto Castilho Piqueira**, Telecommunication and Control Engineering Department, Polytechnic School, The University of São Paulo, 05508-970 São Paulo, Brazil; [piqueira@lac.usp.br](mailto:piqueira@lac.usp.br)

**Elbert E. Neher Macau**, Laboratório Associado de Matemática Aplicada e Computação (LAC), Instituto Nacional de Pesquisas Espaciais (INPE), São José dos Campos, 12227-010 São Paulo, Brazil ; [elbert@lac.inpe.br](mailto:elbert@lac.inpe.br)

**Celso Grebogi**, Department of Physics, King's College, University of Aberdeen, Aberdeen AB24 3UE, UK; [grebogi@abdn.ac.uk](mailto:grebogi@abdn.ac.uk)