

MATRIX MEASURE AND APPLICATION TO STABILITY OF MATRICES AND INTERVAL DYNAMICAL SYSTEMS

ZIAD ZAHREDDINE

Received 27 February 2002

Using some properties of the matrix measure, we obtain a general condition for the stability of a convex hull of matrices that will be applied to study the stability of interval dynamical systems. Some classical results from stability theory are reproduced and extended. We present a relationship between the matrix measure and the real parts of the eigenvalues that make it possible to obtain stability criteria.

2000 Mathematics Subject Classification: 15A48, 37C75, 93D20, 93D09.

1. Introduction. Matrix stability plays an important role in mathematical analysis and its numerous applications to the areas of control theory, differential equations, and linear algebra. The concept of stability itself can be defined in many different ways depending on the context. Of special importance are stable (semistable) matrices—those whose eigenvalues have negative (nonpositive) real parts. A matrix M is D -stable if $D \cdot M$ is stable for every choice of a positive diagonal matrix D . The notion of D -stability of a real square matrix was introduced mathematical economists Arrow and MacManus [2] in studying stability of equilibria in competitive market dynamic models. Relations between stability and D -stability were considered in [2, 7]. Another important stability concept is that of strong stability that arises when diffusion models of biological systems are linearized at a constant equilibrium. Solutions to most of the above problems depend on the stability of linear dynamical system of the form $dx/dt = A \cdot X$, which is studied on the basis of qualitative data on the entries of the matrix as in [13].

The stability of a linear dynamical system is determined by the eigenvalues of the system matrix. When the parameters in the system matrix are uncertain, we are interested in the stability of the matrix given this uncertainty. First studies in this area were realized by Chebyshev and Markov (see a survey of their works in [4]). The most interesting case is when the uncertainty in each parameter in the system matrix is modeled by an interval, that is, the lower and upper bounds are known. A natural conjecture would be that the family of system matrices is stable if and only if all the vertex matrices are stable. In [8, 9], sufficient conditions have been obtained, for which the above conjecture is true in the discrete case. In [5], an extension of Gershgorin's circle theorem

was used to obtain a simple sufficient condition for the stability of the family of system matrices. The same theorem was also used in [1] to obtain more sufficient conditions. When the vertices of the matrix family are symmetric, the corresponding uncertain dynamical systems are stable if and only if the vertex matrices are stable, see [12]. In [10], Kharitonov presented a necessary and sufficient condition for the stability of dynamical systems whose parametric uncertainty is restricted to a rectangular domain. A more general version was discussed in [14], where the rectangular domain was replaced by a pathwise connected region Γ in the complex plane. The concept of Γ -stability was then introduced, and necessary and sufficient conditions for the Γ -stability of a family of systems of differential equations were established. The results of [14] were generalized in [11].

In this paper, we prove a very general sufficient condition for a matrix family such that the stability of a finitely many well-chosen matrices guarantees stability of the convex hull and positive cone of the whole matrix family. This result implies the results in [1, 8, 12]. In some special cases dealing with the stability of interval dynamical systems, the condition becomes necessary as well as sufficient. Illustrative examples will be given.

2. Main results. Consider the convex hull of $n \times n$ matrices in the set $\mathbb{R}^{n \times n}$ described by

$$C = \left\{ M \mid M = \sum_{j=1}^m \gamma_j M_j, \gamma_j \geq 0, \sum_{j=1}^m \gamma_j = 1 \right\}. \quad (2.1)$$

The matrix M is said to be stable if all of its eigenvalues have negative real parts. We say that C is stable if each matrix in C is stable. In what follows, Re denotes the real part of a complex number and $\lambda(M)$ or $\lambda_j(M)$ denotes the eigenvalue of the matrix M . To state our results, some definitions are required.

Let $\|x\|$ denote a vector norm of x on \mathbb{C}^n , and let $\|M\|$ be the induced matrix norm of M given by the vector norm $\|\cdot\|$. Let $\mu(M)$ be the matrix measure of M defined as

$$\mu(M) = \lim_{\theta \rightarrow 0^+} \frac{\|I + \theta M\| - I}{\theta}, \quad (2.2)$$

where I is the identity matrix. The following well-known Coppel inequality [3] gives an upper bound for the magnitude of the solution of a differential equation $\dot{y}(t) = M(t)y(t)$ in terms of the matrix measure

$$\|y(t)\| \leq \|y(t_0)\| \exp \left(\int_{t_0}^t \mu(M(\tau)) d\tau \right), \quad (2.3)$$

which proves useful in the discussions to follow. The next lemma may be found in [3].

LEMMA 2.1. *The matrix measure $\mu(M)$ is well defined for any norm and has the following properties:*

(a) μ is convex on $\mathbb{C}^{n \times n}$, that is, for any $\gamma_j \geq 0$ ($1 \leq j \leq k$), $\sum_{j=1}^k \gamma_j = 1$, and any matrices M_j ($1 \leq j \leq k$), we have

$$\mu \left(\sum_{j=1}^k \gamma_j M_j \right) \leq \sum_{j=1}^k \gamma_j \mu(M_j); \tag{2.4}$$

(b) for any norm and any M , we have

$$-\|M\| \leq -\mu(-M) \leq \operatorname{Re} \lambda(M) \leq \mu(M) \leq \|M\|; \tag{2.5}$$

(c) for the 1-norm $\|x\|_1 = \sum_{j=1}^n |x_j|$, the induced matrix measure μ_1 is given by

$$\mu_1(M) = \max_j \left[\operatorname{Re}(m_{jj}) + \sum_{i \neq j} |m_{ij}| \right], \tag{2.6}$$

for the 2-norm $\|x\|_2 = (\sum_{j=1}^n |x_j|^2)^{1/2}$, the induced matrix measure μ_2 is given by

$$\mu_2(M) = \max_i \left[\frac{\lambda_i(M + M^*)}{2} \right], \tag{2.7}$$

and for the ∞ -norm $\|x\|_\infty = \max_{1 \leq j \leq n} |x_j|$, the induced matrix measure is given by

$$\mu_\infty(M) = \max_i \left[\operatorname{Re}(m_{ii}) + \sum_{j \neq i} |m_{ij}| \right]; \tag{2.8}$$

(d) for any nonsingular matrix N and any vector norm $\|\cdot\|$, with the induced matrix measure μ , $\|N\cdot\|$ defines another vector norm and its induced matrix measure μ_N is given by

$$\mu_N(M) = \mu(NMN^{-1}). \tag{2.9}$$

THEOREM 2.2. *If there exists a norm such that $\mu(M_j) < 0$ ($1 \leq j \leq m$), then C is stable.*

PROOF. Let M be any matrix in C , then there exist $\gamma_j \geq 0$ and $\sum_{j=1}^m \gamma_j = 1$, so that $M = \sum_{j=1}^m \gamma_j M_j$. Since μ is convex and $M \in C$, we have

$$\mu(M) \leq \sum_{j=1}^m \gamma_j \mu(M_j) < 0. \tag{2.10}$$

Then by [Lemma 2.1\(b\)](#), we have $\operatorname{Re} \lambda_j(M) \leq \mu(M) < 0$, which implies that M is stable. Therefore, C is stable and this completes the proof. \square

The previous result can be generalized to the case where M is in a positive cone. Let

$$P = \left\{ M \mid M = \sum_{j=1}^m \gamma_j M_j \mid \gamma_j \geq 0, M \neq 0 \right\} \quad (2.11)$$

be a cone of matrices, which we refer to as a positive cone, then P is said to be stable if each nonzero matrix in P is stable. The following theorem follows.

THEOREM 2.3. *If there exists a matrix measure μ such that $\mu(M_j) < 0$ for $1 \leq j \leq m$, then P is stable.*

PROOF. The matrix measure enjoys the following properties that can be found in [\[3\]](#):

- (1) $\mu(A+B) \leq \mu(A) + \mu(B)$ for any two matrices A and B ,
- (2) $\mu(\alpha A) = \alpha \mu(A)$ for any A and any $\alpha \geq 0$,

from which the proof of the theorem follows directly. \square

Although the conditions of [Theorems 2.2](#) and [2.3](#) are only sufficient, for a certain class of vertices they become also necessary. Let $*$ denote the complex conjugate transpose operation, and let S be a set of matrices. We say that S is $*$ -closed if $M^* \in S$ for any $M \in S$. This leads to the following theorem.

THEOREM 2.4. *Let V be the set of vertex matrices for a convex hull of matrices C , and let V be $*$ -closed. Then, C is stable if and only if there exists a matrix measure μ such that $\mu(M) < 0$ for any $M \in V$.*

PROOF. The sufficiency is guaranteed by [Theorem 2.2](#). To prove necessity, we choose the vector 2-norm. For any $M \in V$, we have $M^* \in V$ since V is $*$ -closed. Since C is stable, $(M + M^*)/2$ is stable, that is, $\max_j \lambda_j(M + M^*)/2 < 0$. From [Lemma 2.1\(c\)](#), we conclude that $\mu_2(M) < 0$ and the proof is complete. \square

Of special interest is the following list of corollaries.

COROLLARY 2.5. *If the vertex matrices are normal, then C is stable if and only if V is stable.*

PROOF. To prove sufficiency, let $M \in V$. Since M is normal, then by [\[6, Theorem 2.5.4\]](#) M can be diagonalized using a unitary transformation, that is, there exists a unitary matrix U such that $M = UDU^{-1}$. Using the 2-norm, which is invariant under a unitary transformation, the induced matrix measure is also invariant; therefore,

$$\mu_2(M) = \mu_2(UDU^{-1}) = \mu_2(D) = \max_j \operatorname{Re} \lambda_j(D) = \max_j \operatorname{Re} \lambda_j(M). \quad (2.12)$$

Hence, if M is stable, then $\mu_2(M) < 0$ for any $M \in V$, and from [Theorem 2.2](#) we conclude that C is stable.

Since necessity is trivial, the proof is then complete. □

The main results of [12] can now be given in the next corollary, the proof of which follows directly from [Theorem 2.4](#).

COROLLARY 2.6. *If the vertex matrices are symmetric, then C is stable if and only if V is stable.*

The next corollary represents one of the main results of [8], and can now be directly concluded from [Theorem 2.2](#) by choosing the vector 2-norm.

COROLLARY 2.7. *If for any $M \in V$, $(M + M^T)/2$ is stable, then C is stable.*

A more general case than [Corollary 2.7](#) is the following result.

COROLLARY 2.8. *If there exists a positive matrix H such that $HM + M^TH$ is stable for any $M \in V$, then C is stable.*

PROOF. If H is positive definite, let $H = K^2$, where K is also positive definite; then, if we use the norm $\|x\| = \|Kx\|_2$, the induced matrix measure μ_K is given by

$$\begin{aligned} \mu_K(M) &= \mu_2(KMK^{-1}) = \max_j \operatorname{Re} \lambda_j \left(\frac{KMK^{-1} + K^{-T}M^TK^T}{2} \right) \\ &= \max_j \operatorname{Re} \lambda_j \left(K^{-1} \frac{HM + M^TH}{2} K^{-1} \right) \leq \frac{\max_j \lambda_j(HM + M^TH)}{2\alpha(H, M)}, \end{aligned} \tag{2.13}$$

where $\alpha(H, M) = \max_j \lambda_j(H)$ if $HM + M^TH$ is negative semidefinite and $\alpha(H, M) = \min_j \lambda_j(H)$ if $HM + M^TH$ is positive semidefinite. If $HM + M^TH$ is stable for any $M \in V$, then it is negative definite; hence $\mu_K(M) < 0$ for any $M \in V$. From [Theorem 2.2](#), it follows that C is stable. □

Now, the main results of [1] follow directly from [Theorem 2.2](#) as shown below.

COROLLARY 2.9. *Let $C_0 = \sum_{j=1}^m M_j/m$. Suppose that there exists a nonsingular N such that NC_0N^{-1} is diagonal. Then if there exists a matrix measure μ such that $\mu(NM_jN^{-1}) < 0$ ($1 \leq j \leq m$), C is stable.*

PROOF. For any norm $|\cdot|$ with N nonsingular, choose a new norm $\rho(x) = |Nx|$. The new induced matrix measure is $\mu_\rho(M) = \mu(NMN^{-1})$ by [Theorem 2.2](#), and the proof is complete. □

The above results can be applied to the stability of interval matrices. Let $L = (l_{ij})$, $U = (u_{ij})$, and $M = (m_{ij})$ be real matrices, and let $L \leq M \leq U$ hold elementwise.

Define

$$\begin{aligned} K &= \{M \mid L \leq M \leq U\} = \{(m_{ij}) \mid l_{ij} \leq m_{ij} \leq u_{ij}\}, \\ V &= \{M \mid m_{ij} = l_{ij} \text{ or } m_{ij} = u_{ij}\}, \end{aligned} \quad (2.14)$$

that is, V is the set of vertex matrices of K . Then, the following result follows from [Theorem 2.2](#).

COROLLARY 2.10. *If there exists a matrix measure μ such that $\mu(M) < 0$ for any $M \in V$, then K is stable.*

The criteria developed in this paper may seem restricted because the matrix measure is only an upper bound of the real parts of the eigenvalues of a matrix. The next theorem will establish a relationship between the real parts of the eigenvalues and the matrix measure, showing that if the matrix measure is properly chosen, then it will be possible to obtain stability criteria which are equivalent to testing the real parts of the eigenvalues for negativity.

THEOREM 2.11. *Let \mathcal{N} be the set of all vector norms on \mathbb{C}^n ; for any $\rho \in \mathcal{N}$, the corresponding matrix measure is denoted by μ_ρ ; then for any matrix in $\mathbb{C}^{n \times n}$, we have*

$$\max_{1 \leq j \leq n} \operatorname{Re} \lambda_j(M) = \inf_{\rho \in \mathcal{N}} \mu_\rho(M). \quad (2.15)$$

PROOF. Let J be the Jordan form of M , then from Jordan's theorem, there exists a nonsingular matrix N such that $J = NMN^{-1} = D + U$, where D is diagonal and U is a matrix whose diagonal elements are zeros and off-diagonal elements are the same as J .

Let $\Lambda = \operatorname{diag}\{1, \sigma^{-1}, \sigma^{-2}, \dots, \sigma^{-(n-1)}\}$ for any positive real σ , then

$$\Lambda J \Lambda^{-1} = D + \sigma U. \quad (2.16)$$

Define a new norm of \mathbb{C}^n by $|x| = |\Lambda N x|_2$. Then the corresponding matrix norm of $I + \gamma M$, where I denotes the identity matrix and γ is any positive number, is

$$\|I + \gamma M\| = \max_{|x|=1} |(I + \gamma M)x| = \max_{|\Lambda N x|_2=1} |\Lambda N(I + \gamma M)x|_2. \quad (2.17)$$

Note that if we let $z = \Lambda N x$, then we have

$$\Lambda N(I + \gamma M)x = \Lambda N(I + \gamma M)N^{-1}\Lambda^{-1}z = I + \gamma(D + \sigma U)z; \quad (2.18)$$

so the corresponding matrix measure of M is

$$\begin{aligned} \mu(M) &= \lim_{y \rightarrow 0} \frac{\|I + yM\| - 1}{y} = \lim_{y \rightarrow 0} \frac{\max_{|z|_2=1} |z + y(D + \sigma U)z|_2 - 1}{y} \\ &\leq \lim_{y \rightarrow 0} \frac{\max_{|z|_2=1} (|(I + yD)z|_2 + \sigma y|Uz|_2) - 1}{y} = \mu_2(D) + \sigma|U|_2 \quad (2.19) \\ &\leq \max_j \operatorname{Re} \lambda_j(M) + \sigma. \end{aligned}$$

Therefore, for any positive real σ , there exists a norm ρ such that

$$\mu_\rho(M) < \max_{1 \leq j \leq n} \operatorname{Re} \lambda_j(M) + \sigma, \quad (2.20)$$

and the proof is thus complete. □

The above theorem suggests that in order to obtain the tightest stability bounds, the norm in [Theorem 2.2](#) must be chosen properly. One possible choice is the class given by the norms $|x|_N = |Nx|_2$ for any nonsingular matrix N . The induced matrix measure is $\mu_N(M) = \mu_2(NMN^{-1})$. This relates to the representation problem for the matrix M . For the stability of interval polynomials, it is interesting to note that the stability of the system depends on finding a suitable state space realization so that the results of [Theorem 2.2](#) can be applied. Now, we state an obvious corollary of [Theorem 2.11](#).

COROLLARY 2.12. *The matrix M is stable if and only if there exists a matrix measure μ such that $\mu(M) < 0$.*

Of special interest is the stability of time-invariant linear systems with parameter variations for unmodeled dynamics. Using the concept of the matrix measure, we can obtain the following result.

THEOREM 2.13. *Suppose that the dynamical system is described by*

$$\dot{x}(t) = (M + \Delta M)x(t), \quad (2.21)$$

where ΔM represents the unmodeled dynamics, then the system is stable if the unmodeled dynamics satisfies the conditions

$$\mu(\Delta M) < -\mu(M), \quad (2.22)$$

where μ is a certain matrix measure.

The proof follows directly from the property $\mu(A + B) \leq \mu(A) + \mu(B)$.

The next corollary shows that our results can be used to test stability of a convex hull of triangular vertex matrices.

COROLLARY 2.14. *If the vertex matrices can be simultaneously transformed by a similarity transformation to upper (or lower) triangular form, then a necessary and sufficient condition for C to be stable is that the vertex matrices are stable.*

PROOF. Without loss of generality, we assume that all vertex matrices M_1, M_2, \dots, M_r are upper triangular. Let $M_k = (m_{ij}^k)$ ($k = 1, 2, \dots, r$) and $D = \text{diag}\{d_1, d_2, \dots, d_n\}$. Let μ denote the matrix measure induced by the vector norm $\|D^{-1}x\|_\infty$. Since

$$D^{-1}M_k D = \begin{pmatrix} m_{11}^k & (d_2/d_1)m_{12}^k & \cdots & (d_n/d_1)m_{1n}^k \\ & m_{22}^k & \cdots & (d_n/d_2)m_{2n}^k \\ & & \ddots & \vdots \\ & & & m_{nn}^k \end{pmatrix}, \quad k = 1, 2, \dots, r, \quad (2.23)$$

we obtain from [Lemma 2.1](#)(c) and (d)

$$\mu(M_k) = \mu_\infty(D^{-1}M_k D) = \max_j \left[\text{Re} \left(m_{ii}^k + \sum_{j>i} \left(\frac{d_j}{d_i} \right) |m_{ij}^k| \right) \right]. \quad (2.24)$$

Let $d_j = \sigma^j$ ($j = 0, 1, \dots, n-1$), where σ is a sufficiently small number. Define $S = \max_{1 \leq k \leq r} \max_{i,j} |m_{ij}^k|$. Then we have

$$\mu(M_k) \leq \max_j \left[\text{Re} \left(m_{ii}^k + S \sum_{j>i} \frac{d_j}{d_i} \right) \right] \leq \max_i [m_{ii}^k] + nS\sigma. \quad (2.25)$$

Therefore, if M_k is stable, then we can choose $\sigma > 0$ sufficiently small so that $\mu(M_k) < 0$ for any $k = 1, 2, \dots, r$. It follows from [Theorem 2.2](#) that C is stable. The necessary part of the theorem is trivial. \square

COROLLARY 2.15. *If the vertex matrices commute, then C is stable if and only if the vertex matrices are stable.*

PROOF. By [\[6, Theorem 2.3.3\]](#), if a family of matrices commute, then they can be simultaneously transformed to upper triangular form. Then, [Corollary 2.14](#) leads to the desired result. \square

We end up with the following corollary, whose proof is straightforward.

COROLLARY 2.16. *If the vertex matrices can be simultaneously transformed to Jordan form, then C is stable if and only if the vertex matrices are stable.*

3. Examples

EXAMPLE 3.1. Let

$$M_1 = \begin{pmatrix} 0 & 1 \\ -2 & -3 \end{pmatrix}, \quad M_2 = \begin{pmatrix} -12 & -3 \\ 4 & 5 \end{pmatrix}, \quad N = \begin{pmatrix} 2 & 1 \\ -1 & -1 \end{pmatrix}. \quad (3.1)$$

Then,

$$NM_1N^{-1} = \begin{pmatrix} -1 & 0 \\ 0 & -2 \end{pmatrix}, \quad NM_2N^{-1} = \begin{pmatrix} -9 & 2 \\ 0 & -8 \end{pmatrix}. \quad (3.2)$$

Define the vector norm $|x| = |N_x|_2$. Then the induced matrix measure is $\mu(M) = \mu_2(NMN^{-1})$. Thus $\mu(M_1) = -1 < 0$ and $\mu(M_2) = -7.382 < 0$, and from [Theorem 2.2](#), we conclude that C is stable.

REMARK 3.2. Since $\mu_2(M_1) = 0.081 > 0$, we cannot use Jiang's results [\[8\]](#). Note also that for $D = \text{diag}\{d_1, d_2\}$, $\mu_D(M) = \mu_\infty(D^{-1}MD)$, which is the matrix measure induced by the vector norm $\|D^{-1}\|_\infty$. Then for any positive numbers d_1 and d_2 ,

$$\mu_D(M_2) = \mu_\infty(D^{-1}M_2D) = 4(d_1/d_2) + 5 > 0. \quad (3.3)$$

Hence, Heinen's results [\[5\]](#) fail the stability test.

EXAMPLE 3.3. Consider the interval dynamical system

$$\dot{x}(t) = Mx(t), \quad (3.4)$$

where

$$M \in M_1 = \begin{pmatrix} [-5, -3] & [1, 2] \\ [4, 5] & [-6, -4] \end{pmatrix}. \quad (3.5)$$

From the observation that

$$\mu_2\left(\begin{pmatrix} -3 & 2 \\ 7 & -4 \end{pmatrix}\right) = \frac{1}{2}(-7 + \sqrt{82}) > 0, \quad (3.6)$$

it follows that the criterion which uses the 2-norm measure developed in [\[8\]](#) cannot be used to study the stability of M_I .

Choose $D = \text{diag}\{1, 0.5\}$. Then

$$DM_I D^{-1} = \begin{pmatrix} [-5, -3] & [2, 4] \\ [2, 2.5] & [-6, -4] \end{pmatrix}. \quad (3.7)$$

Let

$$L = \begin{pmatrix} -5 & 2 \\ 2 & -6 \end{pmatrix}, \quad U = \begin{pmatrix} -3 & 4 \\ 2.5 & -4 \end{pmatrix}, \quad V = \{M \mid m_{ij} = l_{ij}u_{ij}\}. \quad (3.8)$$

For all $M \in V$, the characteristic polynomial of $M^T + M$ is

$$\lambda^2 - 2(m_{11} + m_{22})\lambda + 4m_{11}m_{22} - (m_{12} + m_{21})^2. \quad (3.9)$$

Since $m_{11} < 0$ and $m_{22} < 0$, it follows that

$$\mu_D(M) < 0 \iff M + M^T \text{ stable} \iff 4m_{11}m_{22} - (m_{12} + m_{21})^2 > 0. \quad (3.10)$$

For all $M \in V$,

$$\begin{aligned} & 4m_{11}m_{22} - (m_{12} + m_{21})^2 \\ & \geq 4(-3)(-4) - (4 + 2.5)^2 > 0 \iff \mu_D(M) < 0 \iff M_I \text{ is stable.} \end{aligned} \quad (3.11)$$

Therefore, our criterion is applicable where that of [8] fails.

EXAMPLE 3.4. Consider

$$\mathcal{U} = \left\{ \Delta M \mid \Delta M = \sum_{j=1}^r \alpha_j M_j, \quad |\alpha_j| \leq \beta_j, \quad j = 1, 2, \dots, r \right\}, \quad (3.12)$$

where the matrices M_i , which represent the uncertain structure, are given skew matrices, that is, $M_j^T = -M_j$ ($j = 1, 2, \dots, r$). The problem is to find conditions such that $M + \Delta M$ is asymptotically stable for any $\Delta M \in \mathcal{U}$ (in this case, we say that $M + \mathcal{U}$ is stable), where M satisfies $M + M^T$ is negative definite. The above formulation can be viewed as the representation of a dissipative system with energy-conserving perturbation. If we choose the 2-norm, the induced matrix measure is μ_2 , which satisfies $\mu_2(M + \Delta M) = (1/2)\lambda_{\max}(M + M^T) < 0$; so under the above assumption, we conclude that $M + \mathcal{U}$ is stable with a convergence rate at least $-\mu_2(M)$.

4. Conclusion. In this paper, we have obtained a very general sufficient condition for the stability of a convex hull of matrices and a positive cone of matrices. For a certain class of vertex matrices, the sufficient condition becomes also necessary. Another sufficient condition for the stability of an interval dynamical system is given, and the relationship between the real parts of the eigenvalues of a matrix and its matrix measure is derived. Using the matrix measure, we have also found a result for the stability of time-invariant linear systems with parameter variations representing the unmodeled dynamics.

REFERENCES

- [1] M. B. Argoun, *On sufficient conditions for the stability of interval matrices*, Internat. J. Control **44** (1986), no. 5, 1245–1250.
- [2] K. J. Arrow and M. McManus, *A note on dynamic stability*, Econometrica **26** (1958), 448–454.
- [3] C. A. Desoer and M. Vidyasagar, *Feedback Systems: Input-Output Properties*, Electrical Science, Academic Press, New York, 1975.

- [4] F. R. Gantmacher, *The Theory of Matrices. Vol. 2*, Chelsea Publishing, New York, 1959.
- [5] J. A. Heinen, *Sufficient conditions for stability of interval matrices*, Internat. J. Control **39** (1984), no. 6, 1323–1328.
- [6] R. A. Horn and C. R. Johnson, *Matrix Analysis*, Cambridge University Press, Cambridge, 1985.
- [7] J. L. Howland, *The method of quadratic forms in dynamic stability problems*, Third Canadian Conference in Applied Mechanics (Calgary), 1971.
- [8] C. L. Jiang, *Sufficient condition for the asymptotic stability of interval matrices*, Internat. J. Control **46** (1987), no. 5, 1803–1810.
- [9] ———, *Sufficient and necessary condition for the asymptotic stability of discrete linear interval systems*, Internat. J. Control **47** (1988), no. 5, 1563–1565.
- [10] V. L. Kharitonov, *The asymptotic stability of the equilibrium state of a family of systems of linear differential equations*, Differentsial'nye Uravneniya **14** (1978), no. 11, 2086–2088.
- [11] J. Mawhin, *Some remarks on the Ω -stability for families of polynomials*, Arch. Math. (Brno) **33** (1997), no. 1-2, 139–145.
- [12] Z. C. Shi and W. B. Gao, *A necessary and sufficient condition for the positive-definiteness of interval symmetric matrices*, Internat. J. Control **43** (1986), no. 1, 325–328.
- [13] Z. Zahreddine, *An extension of the Routh array for the asymptotic stability of a system of differential equations with complex coefficients*, Appl. Anal. **49** (1993), no. 1-2, 61–72.
- [14] ———, *On the Γ -stability of systems of differential equations in the Routh-Hurwitz and the Schur-Cohn cases*, Bull. Belg. Math. Soc. Simon Stevin **3** (1996), no. 3, 363–368.

Ziad Zahreddine: Department of Basic Sciences, College of Arts and Sciences, University of Sharjah, Sharjah P.O. 27272, United Arab Emirates

E-mail address: ziadzahr@sharjah.ac.ae

Special Issue on Boundary Value Problems on Time Scales

Call for Papers

The study of dynamic equations on a time scale goes back to its founder Stefan Hilger (1988), and is a new area of still fairly theoretical exploration in mathematics. Motivating the subject is the notion that dynamic equations on time scales can build bridges between continuous and discrete mathematics; moreover, it often reveals the reasons for the discrepancies between two theories.

In recent years, the study of dynamic equations has led to several important applications, for example, in the study of insect population models, neural network, heat transfer, and epidemic models. This special issue will contain new researches and survey articles on Boundary Value Problems on Time Scales. In particular, it will focus on the following topics:

- Existence, uniqueness, and multiplicity of solutions
- Comparison principles
- Variational methods
- Mathematical models
- Biological and medical applications
- Numerical and simulation applications

Before submission authors should carefully read over the journal's Author Guidelines, which are located at <http://www.hindawi.com/journals/ade/guidelines.html>. Authors should follow the Advances in Difference Equations manuscript format described at the journal site <http://www.hindawi.com/journals/ade/>. Articles published in this Special Issue shall be subject to a reduced Article Processing Charge of €200 per article. Prospective authors should submit an electronic copy of their complete manuscript through the journal Manuscript Tracking System at <http://mts.hindawi.com/> according to the following timetable:

Manuscript Due	April 1, 2009
First Round of Reviews	July 1, 2009
Publication Date	October 1, 2009

Lead Guest Editor

Alberto Cabada, Departamento de Análise Matemática, Universidade de Santiago de Compostela, 15782 Santiago de Compostela, Spain; alberto.cabada@usc.es

Guest Editor

Victoria Otero-Espinar, Departamento de Análise Matemática, Universidade de Santiago de Compostela, 15782 Santiago de Compostela, Spain; mvictoria.otero@usc.es